

TPS78601/TPS79501/TPS79601DRB Evaluation Module

This user's guide describes the characteristics, operation, and use of the TPS78601DRBEVM, TPS79501DRBEVM and TPS7960DRBEVM (or TPS7xx01DRBEVM). These EVMs demonstrate the operation and use of Texas Instruments' [TPS78601](#), [TPS79501](#) and [TPS79601](#) low dropout linear regulators (LDOs), all in 3.00 mm x 3.00 mm SON-8 packages, which are capable of 1.5 A, 500 mA, and 1 A of output current, respectively. This user's guide includes setup instructions, a schematic diagram, thermal guidelines, a bill of materials (BOM), and printed circuit board (PCB) layout drawings for the evaluation module. Throughout this document, the abbreviation *EVM* and the term *evaluation module* are synonymous with the TPS7xx01DRBEVM, unless otherwise noted.

Contents

1	Introduction	1
2	Setup	2
3	Operation	2
4	Thermal Guidelines	3
5	Board Layout	4
6	Schematic and Bill of Materials	6

List of Figures

1	Top Layer Assembly	4
2	Top Layer Routing	5
3	Bottom Layer Routing	5
4	TPS7xx01DRBEVM Schematic	6

1 Introduction

The TPS7xx01DRBEVM helps designers evaluate the operation and performance of the LDOs

[Table 1](#) shows related devices.

Table 1. Related Devices

DEVICE	PACKAGE SIZE	ASSEMBLY	DESCRIPTION
TPS78601DRB	3.00 mm x 3.00 mm SON	HPA497-001	Ultra-Low Noise, High-PSRR, Fast-RF, 1.5 A, Low-Dropout Linear Regulator
TPS79501DRB	3.00 mm x 3.00 mm SON	HPA497-002	Ultra-Low Noise, High-PSRR, Fast-RF, 500 mA, Low-Dropout Linear Regulator
TPS79601DRB	3.00 mm x 3.00 mm SON	HPA497-003	Ultra-Low Noise, High-PSRR, Fast-RF, 1.0 A, Low-Dropout Linear Regulator

2 Setup

!- [Section 2](#) describes the jumpers and connectors on the EVM and how to properly connect, set up, and use the TPS7xx01DRBEVM.

2.1 Input / Output Connector Descriptions

J1: VIN

This connector is the positive input supply voltage. The leads to the input supply should be twisted and kept as short as possible to minimize EMI transmission. Additional bulk capacitance should be added between J1 and J2 if the supply leads are greater than six inches. A capacitor with a value of 47 μ F or greater improves the transient response of the TPS7xx01DRB device and helps to reduce ringing on the input when long supply wires are used.

J2: GND

This is the return connection for the output.

J3: GND

This is the return connection for the input power supply of the regulator.

J4: VOUT

This is the positive connection from the output. Connect this pin to the positive input of the load.

J5: EN

This jumper is used to enable or disable the output of the TPS7xx01DRB device. Placing a shorting jumper between pins 1 and 2 (ON position) enables the TPS7xx01DRB device. Placing the shorting jumper between pins 2 and 3 (OFF position) disables the TPS7xx01DRB device.

J6: Output Voltage Select

This jumper sets the desired output voltage from the TPS7xx01DRB device. Placing a shorting jumper between the appropriate pins gives the outputs shown in [Table 2](#).

Table 2. Output Voltage Settings

SHORT PINS:	V _{OUT}
1 and 2	3.3V
3 and 4	2.8V
5 and 6	2.5V
7 and 8	1.8V

3 Operation

[Section 3](#) provides information about the operation of the TPS7xx01DRBEVM.

3.1 General Operation

Connect the positive input power supply to J1. Connect the input power return (ground) to J3. The TPS7xx01DRB device has an absolute maximum input voltage of 6 V. TI recommends a maximum output voltage of 6 V. The highest input voltage may be less than 5.5 V because of thermal conditions. See the [Thermal Considerations](#) section of this manual to determine the highest input voltage.

Connect the desired load between J4 (positive lead) and J2 (negative or return lead). Configure jumper J6 for the desired output voltage.

4 Thermal Guidelines

[Section 4](#) provides guidelines for the thermal management of the TPS7xx01DRBEVM board.

4.1 Thermal Considerations

Thermal management is a key design component of any power converter and is especially important when the power dissipation in the LDO is high. To better help you design the TPS7xx01DRB family into your application, the following formula should be used to approximate the maximum power dissipation at a particular ambient temperature:

$$T_J = T_A + P_D \times \theta_{JA}$$

Where:

T_J = junction temperature

T_A = ambient temperature

P_D = power dissipation in the IC

θ_{JA} = thermal resistance from junction to ambient

(1)

All temperatures are in degrees Celsius (°C).

The measured thermal resistance from junction to ambient for the TPS7xx01DRBEVM has a typical value of 32°C/W. The recommended maximum operating junction temperature specified in the product data sheets for the TPS7xx01 family is +125°C. With these two pieces of information, the maximum power dissipation can be found by using [Equation 1](#).

[Table 3](#) shows the maximum input voltage that can be applied to the input of the TPS7xx01DRBEVM by device type and selected output voltage. The maximum input voltage shown provides the rated output current while keeping the junction temperature at or below the recommended +125°C. Values for two different ambient temperatures (+25°C and +85°C) are shown.

Table 3. Maximum Input Voltage versus Ambient Temperature and Output Voltage

DEVICE	I _{OUT} (A)	SELECTED OUTPUT VOLTAGE (V) FOR T _A = +25°C				SELECTED OUTPUT VOLTAGE (V) FOR T _A = +85°C			
		1.80	2.50	2.80	3.30	1.80	2.50	2.80	3.30
TPS78601DRB	1.50	3.88	4.58	4.88	5.38	2.63	3.33	3.63	4.13
TPS79501DRB	0.50	5.5 ⁽¹⁾	5.5 ⁽¹⁾	5.5 ⁽¹⁾	5.5 ⁽¹⁾	4.30	5.00	5.30	5.5 ⁽¹⁾
TPS79601DRB	1.00	4.93	5.5 ⁽¹⁾	5.5 ⁽¹⁾	5.5 ⁽¹⁾	3.05	3.75	4.05	4.55

⁽¹⁾ Not limited by thermals; limited by recommended input voltage.

5 Board Layout

!- Section 5 provides the TPS7xx01DRBEVM board layout and illustrations.

5.1 Layout

NOTE: Board layouts are not to scale. These figures are intended to show how the board is laid out, and are not intended to be used for manufacturing TPS7xx01DRBEVM PCBs.

Figure 1 through Figure 3 show the PCB layouts.




Figure 1. Top Layer Assembly




Figure 2. Top Layer Routing




Figure 3. Bottom Layer Routing

6.2 Bill of Materials

Table 4 lists the bill of materials for the TPS7xx01DRBEVM.

Table 4. TPS7xx01DRBEVM Bill of Materials ⁽¹⁾⁽²⁾⁽³⁾

001	002	003	REFDES	VALUE	DESCRIPTION	SIZE	PART NUMBER	MFR
1	1	1	C1	10 μ F	Capacitor, Ceramic, Low Inductance, 6.3 V, X5R, 20%	0603	STD	STD
1	1	1	C2	33 pF	Capacitor, Ceramic, Low Inductance, 50 V, COG, 5%	0603	STD	STD
1	1	1	C3	20 pF	Capacitor, Ceramic, Low Inductance, 50 V, COG, 5%	0603	STD	STD
1	1	1	C4	4.7 μ F	Capacitor, Ceramic, Low Inductance, 6.3 V, X5R, 20%	0603	STD	STD
1	1	1	C5	15 pF	Capacitor, Ceramic, Low Inductance, 50 V, COG, 5%	0603	STD	STD
1	1	1	C7	18 pF	Capacitor, Ceramic, Low Inductance, 50 V, COG, 5%	0603	STD	STD
4	4	4	J1, J2, J3, J4	PEC02SAAN	Header, Male 2-pin, 100-mil spacing	0.100"	PEC02SAAN	Sullins
1	1	1	J5	PEC03SAAN	Header, Male 3-pin, 100-mil spacing	0.100"	PEC03SAAN	Sullins
1	1	1	J6	PEC04DAAN	Header, Male 2 x 4-pin, 100-mil spacing	0.100"	PEC04DAAN	Sullins
1	1	1	R1	30.1 k Ω	Resistor, Chip, 1/16W, 1%	0603	STD	STD
1	1	1	R2	14.0 k Ω	Resistor, Chip, 1/16W, 1%	0603	STD	STD
1	1	1	R3	31.6 k Ω	Resistor, Chip, 1/16W, 1%	0603	STD	STD
1	1	1	R5	51.1 k Ω	Resistor, Chip, 1/16W, 1%	0603	STD	STD
1	1	1	R7	39.2 k Ω	Resistor, Chip, 1/16W, 1%	0603	STD	STD
1	—	—	U1	TPS78601DRB	IC, LDO Linear Regulator Ultralow-Noise High PSRR Fast RF	SON-8	TPS78601DRB	TI
—	1	—	U1	TPS79501DRB	IC, LDO Linear Regulator Ultralow-Noise High PSRR Fast RF	SON-8	TPS79501DRB	TI
—	—	1	U1	TPS79601DRB	IC, LDO Linear Regulator Ultralow-Noise High PSRR Fast RF	SON-8	TPS79601DRB	TI
1	1	1	—	—	PCB, 2.00 in x 2.00 in x 0.062 in	—	HPS497	Any
2	2	2	—	—	Shunt, 100-mil, Black	—	929950-00	3M

⁽¹⁾ These assemblies are ESD sensitive. ESD precautions shall be observed.

⁽²⁾ These assemblies must be clean and free from flux and all contaminants. Use of *no-clean flux* is not acceptable.

⁽³⁾ These assemblies must comply with workmanship standards IPC-A-610 Class 2.

Evaluation Board/Kit Important Notice

Texas Instruments (TI) provides the enclosed product(s) under the following conditions:

This evaluation board/kit is intended for use for **ENGINEERING DEVELOPMENT, DEMONSTRATION, OR EVALUATION PURPOSES ONLY** and is not considered by TI to be a finished end-product fit for general consumer use. Persons handling the product(s) must have electronics training and observe good engineering practice standards. As such, the goods being provided are not intended to be complete in terms of required design-, marketing-, and/or manufacturing-related protective considerations, including product safety and environmental measures typically found in end products that incorporate such semiconductor components or circuit boards. This evaluation board/kit does not fall within the scope of the European Union directives regarding electromagnetic compatibility, restricted substances (RoHS), recycling (WEEE), FCC, CE or UL, and therefore may not meet the technical requirements of these directives or other related directives.

Should this evaluation board/kit not meet the specifications indicated in the User's Guide, the board/kit may be returned within 30 days from the date of delivery for a full refund. **THE FOREGOING WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE.**

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user indemnifies TI from all claims arising from the handling or use of the goods. Due to the open construction of the product, it is the user's responsibility to take any and all appropriate precautions with regard to electrostatic discharge.

EXCEPT TO THE EXTENT OF THE INDEMNITY SET FORTH ABOVE, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

TI currently deals with a variety of customers for products, and therefore our arrangement with the user **is not exclusive.**

TI assumes **no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein.**

Please read the User's Guide and, specifically, the Warnings and Restrictions notice in the User's Guide prior to handling the product. This notice contains important safety information about temperatures and voltages. For additional information on TI's environmental and/or safety programs, please contact the TI application engineer or visit www.ti.com/esh.

No license is granted under any patent right or other intellectual property right of TI covering or relating to any machine, process, or combination in which such TI products or services might be or are used.

FCC Warning

This evaluation board/kit is intended for use for **ENGINEERING DEVELOPMENT, DEMONSTRATION, OR EVALUATION PURPOSES ONLY** and is not considered by TI to be a finished end-product fit for general consumer use. It generates, uses, and can radiate radio frequency energy and has not been tested for compliance with the limits of computing devices pursuant to part 15 of FCC rules, which are designed to provide reasonable protection against radio frequency interference. Operation of this equipment in other environments may cause interference with radio communications, in which case the user at his own expense will be required to take whatever measures may be required to correct this interference.

EVM Warnings and Restrictions

It is important to operate this EVM within the input voltage range of 2.7V to 5.5V and the output voltage range of 1.2V to 5.5V.

Exceeding the specified input range may cause unexpected operation and/or irreversible damage to the EVM. If there are questions concerning the input range, please contact a TI field representative prior to connecting the input power.

Applying loads outside of the specified output range may result in unintended operation and/or possible permanent damage to the EVM. Please consult the EVM User's Guide prior to connecting any load to the EVM output. If there is uncertainty as to the load specification, please contact a TI field representative.

During normal operation, some circuit components may have case temperatures greater than +85°C. The EVM is designed to operate properly with certain components above +85°C as long as the input and output ranges are maintained. These components include but are not limited to linear regulators, switching transistors, pass transistors, and current sense resistors. These types of devices can be identified using the EVM schematic located in the EVM User's Guide. When placing measurement probes near these devices during operation, please be aware that these devices may be very warm to the touch.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2016, Texas Instruments Incorporated

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com